

# PUBLIC ADDRESS MIXER AMPLIFIER PA-120/ PA-200

AN EASY TO USE AND AFFORDABLE MIXER AMPLIFIER TO ADDRESS YOUR REQUIREMENTS OF ANNOUNCEMENT AND BACKGROUND MUSIC APPLICATIONS IN RESTAURANTS, STORES, SCHOOL CLASSROOMS, MEETING ROOMS, OFFICES, PLACES OF WORSHIP AND ANY OTHER COMMERCIAL ENVIRONMENTS **NOW WITH BLUETOOTH**



REMOTE CONTROL FOR MUSIC PLAYER MODULE



FRONT VIEW



REAR VIEW

## SPECIFICATIONS FOR PA -120/ PA-200

- |  |                            |                         |  |
|--|----------------------------|-------------------------|--|
| ● POWER SUPPLY                                   | : AC 230V 50Hz             | ● POWER OUTPUT          | : 120W/ 200W                                   |
| ● SENSITIVITY MIC 1 & MIC 2                      | : 4 mV                     | ● SENSITIVITY AUX 1 & 2 | : 550 mV                                       |
| ● LINE OUT                                       | : 750 mV                   | ● FREQUENCY RESPONSE    | : 60Hz TO 20 KHz + /- 3dB                      |
| ● OUTPUT   | : 100V, 70V, 4 - 16Ω - COM | ● SIGNAL TO NOISE RATIO | : 80 dB  |
| ● VOICE PRIORITY MUTE                            | : MIC 1                    | ● TONE                  | : BASS 100Hz +/- 10 dB, TREBLE 10kHz +/- 10 dB |
| ● AC POWER CONSUMPTION: PA-120-200W/ PA-200-310W |                            | ● MOUNTING              | : FREE STANDING                                |

EITHER MP3 OR AUX 3 CAN BE PLAYED AT ONE TIME. REFRAIN FROM USING AUX 3 IN CASE YOU ARE USING MUSIC PLAYER

- DIMENSIONS : 65 mm (H) X 440 mm (W) X 290 mm (D)