

SCSL18W LED Street light with Dimming

(LED Street light with Dimming Microwave Motion Sensor)



Fitting Type	Led Street light
Power Consumption	50 Watts (when on at full brightness) and 10 Watts when Dim, When ambient light less than 50 Lux the street light will be on 100% when there is no human traffic in range of sensor street light dims to 20% .
Operating Description	Stays on as long as motion detected, then goes to standby mode after 90 seconds of no movement, Sensor range is up to approx. 8 m
Voltage	220-240 V AC 50-60Hz
Lifetime	Up to 35,000+ hours
Colour Temperature	6500K
Pole Dia	
Dimensions	
Body Material	Aluminum Die Cast with Clear PC optical cover
Light Output	5,000 lumen
Dimmable	Yes
Warranty	1 Year